Change the decimal place numbers for WISE-523x / WISE-224x

1. Login to WISE webpage and go to "Security Setting" page.

Web Inside, Sma		WISE-5238M-4GC(新度) 📄 💣 🛃
DAS Web Anywhere, Automa	adon Anywheren	OK G758.3MB(Approx.1031 Days)
System Setting Module Setting	g Logger Setting IoT I	Platform Setting Advanced Setting Rule Setting Channel Status IP Camera Status
System Setting Security Setting		
Time Setting	Administrator Pro	file Setting
Network Setting	*Email Address	
SNMP Setting	Alarm	When the microSD card is abnormal
Account Setting		
Security Setting		Save
COM Port Interface Setting	Local FTP Server	Setting
	Server Status	☑Enable
	Username	admin
	*Password	[FTP1_Admin
		Save
CGI Query Authentication Setting		
	Authentication	☑Enable
	*Username	admin
	*Password	CGI_Admin
		Save

2. Enable "CGI Query Authentication Setting", Save the setting and Download it to the WISE module.

ICP Web Inside, Smar		WISE-5236M-4GC(新店) 📄 🛃 🐔
DAS Web Anywhere, Automa	tion Anywhere!	👔 OK 🏾 🎧 758.3MB(Approx.1031 Days) 🛛 🔤 Instant Message
System Setting Module Setting	Logger Setting IoT	Platform Setting Advanced Setting Rule Setting Channel Status IP Camera Status
System Setting Security Setting		
Time Setting	Administrator Pro	file Setting
Network Setting	*Email Address	
SNMP Setting	Alarm	When the microSD card is abnormal
Account Setting		
Security Setting		Save
COM Port Interface Setting	Local FTP Server	r Setting
	Server Status	✓Enable
	Usemame	admin
	*Password	FTP1_Admin
		Save
	CGI Query Authe	ntication Setting
	Authentication	✓Enable
	*Username	admin
	*Password	CGI_Admin
		Save

 Key in the following command on the URL bar of a browser: http://[IP]/dll/query.dll?id=admin&password=CGI_Admin&job=set_float&d ecimal_place_num=n Please Note : 1. [IP] : The IP address of the WISE.

2. n = 1~4